

Installatiehandleiding

- **Type : Adapter (Onderverdeling : GE, GEM, GS, GSM, GST, OWA, SGA, SGAS, GP, GC, NGE)**

- **Inleiding**

Een adapter is een type extern schakelende voeding, die ontwikkeld is voor het extern aansluiten van elektrisch apparatuur. Mean Well heeft adapters in diverse modellen voor industriële, vochtbestendige en medische toepassingen.

- **Installatie**

- (1) Voordat u de DC-kabel van een adapter op een apparaat aansluit, dient u de AC-kabel van de adapter eruit te halen en te verifiëren, of de eenheid zich binnen de voltage- en stroomwaarden van het apparaat bevindt.
- (2) Zorg dat de verbinding tussen de adapter en de stroomkabel goed vast zit en dat de verbinding met de DC-aansluiting naar het apparaat correct uitgevoerd is.
- (3) Bescherm de stroomkabel zodat men er niet op stapt of dat het geplet wordt.
- (4) Zorg ervoor dat het apparaat tijdens gebruik goed geventileerd wordt om een oververhitting te voorkomen. Houd een afstand van 10-15 cm in acht als het naastgelegen apparaat een hitte bron is.
- (5) Een goedgekeurde stroomkabel dient gelijk aan of groter te zijn dan SVT, 3G×18AWG of H03VV-F, 3G×0.75mm²
- (6) Als het aangesloten apparaat gedurende een langere periode niet wordt gebruikt, dient u het apparaat uit de stroomvoorziening te halen waardoor u een beschadiging door stroompieken of blikseminslag voorkomt.
- (7) Voor overige informatie over onze producten, bezoek onze website www.meanwell.com voor meer details

- **Waarschuwing / wees voorzichtig!!**

- (1) Risico op elektrische schok en gevaren in combinatie met stroom. Iedere storing dient door een gekwalificeerde technicus te worden onderzocht. Verwijder de behuizing van de adapter niet zelfstandig!
- (2) Brandrisico of risico op een elektrische schok. De openingen dienen te worden beschermd tegen vreemde voorwerpen of druppelende vloeistoffen.
- (3) Het gebruik van een verkeerde DC plug of geforceerd aansluiten van de DC plug op een elektrisch apparaat kan schade aan het apparaat of storingen veroorzaken. Bekijk de informatie over de compatibiliteit van de DC plug in de specificatie.
- (4) Adapters dienen op een betrouwbaar oppervlak te worden geplaatst. Gooien of vallen kan schade veroorzaken.
- (5) Plaats geen adapters in een omgeving met een hoge luchtvochtigheid of in de buurt van water.
- (6) Plaats geen adapters in een omgeving met een hoge omgevingstemperatuur of in de buurt van een vuurbron. Kijk in de specificaties voor de maximale omgevingstemperatuur.
- (7) Uitgangsstroom en uitgangswattage mag de aangegeven waarden in de specificatie niet overschrijden.
- (8) Verbreek de verbinding van het apparaat met de AC-stroomkabel voordat u het reinigt. Gebruik geen vloeibare reinigingsmiddelen of reinigingsmiddelen in spuitbussen. Gebruik alleen een vochtig doekje om het apparaat af te vegen.
- (9) Waarschuwing:
 - (a) Apparatuur dat gebruikt maakt van adapters die conform BSMI gecertificeerd zijn, vereisen ontvlambaarheid classificatie V1 of hoger voor omgevingsapparatuur
 - (b) Gebruik van dit apparaat in een woonomgeving kan mogelijk radio interferentie veroorzaken.
- (10) Contacteer uw lokale gekwalificeerde kringloop/recycling bedrijf indien uw het product weg wilt doen

Installatiehandleiding

- (11) Dit product voldoet aan Hoofdstuk 15 van de FCC regels. Gebruik is onderhevig aan de volgende twee condities:
- (a) Dit product veroorzaakt geen schadelijke interferentie en
 - (b) Dit product dient alle interferentie te accepteren inclusief interferentie die mogelijk ongewenste effecten veroorzaakt
- (12) Alleen voor GST360A/B: Oppervlakken die niet hoeven te worden aangeraakt om de apparatuur te bedienen (contacttijd < 1 s).
- (13) Alleen voor NGE: Om aan te geven dat de voedingseenheid niet mag worden gebruikt als de pinnen van het stekker gedeelte beschadigd zijn.

● Energie efficiëntie

Model identifier	GST18A/B/E/U(05/07/09/12/15/18/24/28/48)-P1J
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/7.5/9.0/12.0/15.0/18.0/24.0/28.0/48.0 (V)
Output current	3.0/2.0/2.0/1.5/1.2/1.0/0.75/0.64/0.375 (A)
Output power	15.0W for 5.0/7.0V output 18.0W for other
Average active efficiency	>81.39% for 5V, >85.0% for other
Efficiency at low load (10 %)	>81.6% (typ)
No-load power consumption	<0.10W

Model identifier	GST25A/B/E/U(05/07/09/12/15/18/24/28/48)-P1J
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/7.5/9.0/12.0/15.0/18.0/24.0/28.0/48.0 (V)
Output current	4.0/2.93/2.55/2.08/1.66/1.38/1.04/0.89/0.52(A)
Output power	20.0W for 5.0V, 22.0W for 7.5V, 23.0W for 9.0V, 25.0W for other
Average active efficiency	>83.35% for 5V, >86.35% for other
Efficiency at low load (10 %)	>81.7%(typ)
No-load power consumption	<0.10W

Installatiehandleiding

Model identifier	GST36B/E/U(05/09/12/24/48)-P1J
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/9.0/12.0/24.0/48.0 (V)
Output current	4.3/3.11/3.0/1.5/0.75(A)
Output power	21.5W for 5.0V, 28.0W for 9.0V, 36.0W for other
Average active efficiency	>83.6% for 5V, >87.4% for other
Efficiency at low load (10 %)	>82.4%(typ)
No-load power consumption	<0.10W

Model identifier	GST40A(05/07/09/12/15/18/24/48)-P1J
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/7.5/9.0/12.0/15.0/18.0/24.0/48.0 (V)
Output current	5.0/5.34/4.45/3.34/2.67/2.22/1.67/0.84 (A)
Output power	25.0W for 5.0V 40.0W for other
Average active efficiency	>83.46% for 5V, >87.59% for other
Efficiency at low load (10 %)	>84.54%(typ)
No-load power consumption	<0.10W

Model identifier	GST60A(05/07/09/12/15/18/24/48)-P1J
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/7.5/9.0/12.0/15.0/18.0/24.0/48.0 (V)
Output current	6.0/6.0/6.0/5.0/4.0/3.33/2.5/1.25(A)
Output power	30.0W for 5.0V, 45.0W for 7.5V, 54.0 W for 9.0V, 60.0W for other
Average active efficiency	>85.07% for 5V, > 88% for other
Efficiency at low load (10 %)	>85.0%(typ)
No-load power consumption	<0.21W

Installatiehandleiding

Model identifier	GST90A(12/15/19/24/48)-P1M
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	12.0/15.0/19.0/24.0/48.0 (V)
Output current	6.67/6.0/4.74/3.75/1.87(A)
Output power	80.0W for 12.0V, 90.0W for other
Average active efficiency	>88.0 %
Efficiency at low load (10 %)	>86.1 %(typ)
No-load power consumption	<0.21W

Model identifier	GST120A(12/15/20/24/48)-R7B/P1M
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	12.0/15.0/20.0/24.0/48.0 (V)
Output current	8.5/7.0/6.0/5.0/2.5(A)
Output power	102.0W for 12.0V, 105.0W for 15.0V, 120.0W for other
Average active efficiency	>88.0 %
Efficiency at low load (10 %)	>86.5 %(typ)
No-load power consumption	<0.21W

Model identifier	GST160A(12/15/20/24/48)-R7B
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	12.0/15.0/20.0/24.0/36.0/48.0 (V)
Output current	11.5/9.6/8.0/6.67/4.44/3.34(A)
Output power	138.0W for 12.0V, 144.0W for 15.0V, 160.0W for other
Average active efficiency	>88.0 %
Efficiency at low load (10 %)	>80.0 %(typ)
No-load power consumption	<0.21W

Installatiehandleiding

Model identifier	GST220A(12/15/20/24/36/48)-R7B
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	12.0/15.0/20.0/24.0/36.0/48.0 (V)
Output current	15.0/13.4/11.0/9.2/6.1/4.6(A)
Output power	180.0W for 12.0V, 201.0W for 15.0V, 220.0W for 20.0V, 221.0W for 24.0V, 219.6W for 36.0V, 221.0W for 48.0V
Average active efficiency	>88.0 %
Efficiency at low load (10 %)	>80.0 %(typ)
No-load power consumption	<0.21W

Model identifier	GST280A(12/15/20/24/48)-C6P
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	12.0/15.0/20.0/24.0/48.0(V)
Output current	21.0/17.0/13.0/11.67/5.84(A)
Output power	252.0W for 12.0V,255.0W for 15.0V, 260.0W for 20.0V,280.08W for 24.0V , 280.32W for 48.0V
Average active efficiency	>89.5%
Efficiency at low load (10 %)	>82.5% (typ)
No-load power consumption	<0.50W

Model identifier	GST360A/B(12/15/24/36/48/55)-C6P/C8P
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	12.0/15.0/24.0/36.0/48.0/55.0 (V)
Output current	27.5/22.7/15.0/10.0/7.5/6.55 (A)
Output power	330.0W for 12.0V output, 340.5W for 15.0V output 360.0W for other
Average active efficiency	>88.0%
Efficiency at low load (10 %)	>82.5% (typ)
No-load power consumption	<0.50W

Installatiehandleiding

Model identifier	SGAS06E/U(05/07/09/12/15/24/48)-P1J
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/7.5/9.0/12.0/15.0/24.0/48.0(V)
Output current	1.0/0.8/0.66/0.5/0.4/0.25/0.125(A)
Output power	5.0W for 5.0V, 6W for other
Average active efficiency	>75.91% for 5V, >81.27% for other
Efficiency at low load (10 %)	>72.22%(typ)
No-load power consumption	<0.10W

Model identifier	SGAS15A/B/E/U (05/09/12/15/24)-P1J
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/9.0/12.0/15.0/24.0(V)
Output current	2.4/1.66/1.25/1.0/0.625(A)
Output power	12.0W for 5.0V, 15W for other
Average active efficiency	>81.60% for 5V, >84.92% for other
Efficiency at low load (10 %)	>79.85%(typ)
No-load power consumption	<0.10W

Model identifier	SGAS60E/U (05/12/15/24/48)-P1J
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/12.0/15.0/24.0/48.0(V)
Output current	6.0/5.0/4.0/2.5/1.25(A)
Output power	30.0W for 5.0V, 60W for other
Average active efficiency	>86.22% for 5V, >89.02% for other
Efficiency at low load (10 %)	>84.59%(typ)
No-load power consumption	<0.15W

Notitie:

GSM series voldoet aan de medische standaard 60601-1. Onderstaande efficiëntie parameters zijn voor prestatie referentie.

Installatiehandleiding

Model identifier	GSM06E/U(05/06/07/09/12/15/18/24)-P1J
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/6.0/7.5/9.0/12.0/15.0/18.0/24.0(V)
Output current	1.2/1.0/0.8/0.66/0.5/0.4/0.33/0.25(A)
Output power	6.0W for all
Average active efficiency	>68% for 5.0V, > 74% for other
Efficiency at low load (10 %)	>65% (typ)
No-load power consumption	<0.30W

Model identifier	GSM12U05-P1J/USB,GSM12E/U(07/09/12/15/18/24/48)-P1J
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/7.5/9.0/12.0/15.0/18.0/24.0/48.0(V)
Output current	2.4/1.6/1.33/1.0/0.8/0.66/0.5/0.25(A)
Output power	12.0W for all
Average active efficiency	>80.0%
Efficiency at low load (10 %)	>78% (typ)
No-load power consumption	<0.075W(<0.1W for 18V/48V)

Model identifier	GSM18B/E/U(05/07/09/12/15/18/24/48)-P1J
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/7.5/9.0/12.0/15.0/18.0/24.0//48.0 (V)
Output current	3.0/2.0/2.0/1.5/1.2/1.0/0.75/0.375 (A)
Output power	15.0W for 5.0/7.0V output, 18.0W for other
Average active efficiency	>81.39% for 5V, >85.0% for other
Efficiency at low load (10 %)	>81.6% (typ)
No-load power consumption	<0.10W

Installatiehandleiding

Model identifier	GSM25B/E/U(05/07/09/12/15/18/24/48)-P1J
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/7.5/9.0/12.0/15.0/18.0/24.0/48.0 (V)
Output current	4.0/2.93/2.55/2.08/1.66/1.38/1.04/0.52(A)
Output power	20.0W for 5.0V, 22.0W for 7.5V, 25.0W for other
Average active efficiency	>83.35% for 5V, >86.35% for other
Efficiency at low load (10 %)	>81.7%(typ)
No-load power consumption	<0.10W

Model identifier	GSM36B/E/U(05/07/09/12/15/18/24/48)-P1J
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/9.0/12.0/15.0/18.0/24.0/48.0 (V)
Output current	4.5/4.32/4.0/3.0/2.4/2/1.5/0.75(A)
Output power	22.5W for 5.0V, 32.4W for 7.0V, 36.0W for other
Average active efficiency	>83.6% for 5V, >87.4% for other
Efficiency at low load (10 %)	>82.4%(typ)
No-load power consumption	<0.10W

Model identifier	GSM40A/B(05/07/09/12/15/18/24/48)-P1J
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/7.5/9.0/12.0/15.0/18.0/24.0/48.0 (V)
Output current	5.0/5.34/4.45/3.34/2.67/2.22/1.67/0.84 (A)
Output power	25.0W for 5.0V, 40.0W for other
Average active efficiency	>83.46% for 5V, >87.59% for other
Efficiency at low load (10 %)	>84.54%(typ)
No-load power consumption	<0.10W

Installatiehandleiding

Model identifier	GSM60A/B/E/U(05/07/09/12/15/18/24/48)-P1J
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/7.5/9.0/12.0/15.0/18.0/24.0/48.0 (V)
Output current	6.0/6.0/5.5/4.5/4/3.33/2.5/1.25(A)
Output power	30.0W for 5.0V, 45.0W for 7.5V, 49.5 W for 9.0V, 54.0W for 12V, 60W for other
Average active efficiency	>85.07% for 5V, > 88% for other
Efficiency at low load (10 %)	>85.0%(typ)
No-load power consumption	<0.21W

Model identifier	GSM90A/B(12/15/19/24/48)-P1M
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	12.0/15.0/19.0/24.0/48.0 (V)
Output current	6.67/6.0/4.74/3.75/1.87(A)
Output power	80.0W for 12.0V, 90.0W for other
Average active efficiency	>88.0 %
Efficiency at low load (10 %)	>87.1 %(typ)
No-load power consumption	<0.21W

Model identifier	GSM120A/B(12/15/20/24/48)-R7B
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	12.0/15.0/20.0/24.0/48.0 (V)
Output current	8.5/7.0/6.0/5.0/2.5(A)
Output power	102.0W for 12.0V, 105.0W for 15.0V, 120.0W for other
Average active efficiency	>88.0 %
Efficiency at low load (10 %)	>86.3 %(typ)
No-load power consumption	<0.21W

Installatiehandleiding

Model identifier	GSM160A/B(12/15/20/24/48)-R7B
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	12.0/15.0/20.0/24.0/36.0/48.0 (V)
Output current	11.5/9.6/8.0/6.67/4.44/3.34(A)
Output power	138.0W for 12.0V, 144.0W for 15.0V, 160.0W for other
Average active efficiency	>88.0 %
Efficiency at low load (10 %)	>87.6 %(typ)
No-load power consumption	<0.21W

Model identifier	GSM220A/B(12/15/20/24/48)-R7B
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	12.0/15.0/20.0/24.0/48.0 (V)
Output current	15.0/13.4/11.0/9.2/4.6(A)
Output power	180.0W for 12.0V, 201.0W for 15.0V, 220.0W for 20.0V, 221.0W for other
Average active efficiency	>88.0 %
Efficiency at low load (10 %)	>84.6 %(typ)
No-load power consumption	<0.21W

Model identifier	OWA-60E-12/15/20/24/30/36/42/48/54
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	12.0/15.0/20.0/24.0/30.0/36.0/42.0/48.0/54.0 (V)
Output current	5.0/4.0/3.0/2.5/2.0/1.67/1.5/1.25/1.12(A)
Output power	60.0W for 12.0/15.0/20.0/24.0/30.0/48.0(V), 60.12W for 36.0V, 63.0W for 42.0V, 60.48W for 54.0V
Average active efficiency	>88.0 %
Efficiency at low load (10 %)	>80.0 %(typ)
No-load power consumption	<0.21W

Installatiehandleiding

Model identifier	OWA-90E-12/15/20/24/30/36/42/48/54
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	12.0/15.0/20.0/24.0/30.0/36.0/42.0/48.0/54.0 (V)
Output current	7.5/6.0/4.5/3.75/3.0/2.5/2.15/1.88/1.67 (A)
Output power	90.0W for 12.0/15.0/20.0/24.0/30.0/36.0(V), 90.3W for 42.0V, 90.24W for 48.0V, 90.18W for 54.0V
Average active efficiency	>88.0 %
Efficiency at low load (10 %)	>79.0 %(typ)
No-load power consumption	<0.21W

Model identifier	OWA-120E-(12/15/20/24/30/36/42/48/54)
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	12.0/15.0/20.0/24.0/30.0/36.0/42.0/48.0/54.0 (V)
Output current	9.6/8.0/6.0/5.0/4.0/3.4/2.9/2.5/2.3 (A)
Output power	115W for 12.0V, 120W for 15.0/20.0/24.0/30.0/48.0(V), 122.4W for 36.0V, 121.8W for 42.0V, 124.2W for 54.0V
Average active efficiency	>88.0 %
Efficiency at low load (10 %)	>82.5 %(typ)
No-load power consumption	<0.21W

Model identifier	OWA-200E-(12/20/24/36/42/48/54)
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	12.0/20.0/24.0/36.0/42.0/48.0/54.0(V)
Output current	15.0/10.0/8.3/5.55/4.75/4.17/3.71(A)
Output power	180W for 12.0V, 200W for 20V, 199W for other
Average active efficiency	>91% for 12V, >92.5% for other
Efficiency at low load (10 %)	>87.5%(typ)
No-load power consumption	<0.15W

Installatiehandleiding

Model identifier	GS06E/U-(1/11/2/3/4/5/6/8)
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/7.5/9.0/12.0/15.0/18.0/24.0/48.0 (V)
Output current	1.0/0.8/0.66/0.5/0.4/0.33/0.25/0.125 (A)
Output power	6W
Average active efficiency	>78.88 %
Efficiency at low load (10 %)	>73.0 %(typ)
No-load power consumption	<0.10W

Model identifier	GS15-(1/1-1/2/3/4/5/6/8)
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/7.5/9.0/12.0/15.0/18.0/24.0/48.0 (V)
Output current	2.4/1.6/1.66/1.25/1.0/0.83/0.625/0.31 (A)
Output power	12W for 5.0/7.5V, 15.0W for other
Average active efficiency	>82.96% for 5/7.5V, >84.13% for other
Efficiency at low load (10 %)	>79.0 %(typ)
No-load power consumption	<0.10W

Model identifier	GP25A/B(13A/13D/14E/58F)-R1B
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	(+5.0,+12.0,-5.0)/(+5.0,+12.0,-12.0)/ (+5.0,+15.0,-15.0) / (+16.0,+48.0,-16.0)(V)
Output current	(2.5,1.2,0.3)/(2.5,1.0,0.3)/(2.5,0.8,0.3)/(1.05,0.087,1.05)(A)
Output power	28.5W for 13A,28.0W for 13D,29.0W for 14E, 37.77W for 58F
Average active efficiency	>80% for 13A、13D , > 80.5% for 14E , > 85% for 58F
Efficiency at low load (10 %)	>75.0 %(typ)
No-load power consumption	<0.30W

Installatiehandleiding

Model identifier	GP50A(13A/13D/14E/58F)-R1B
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	(+5.0,+12.0,-5.0)/(+5.0,+12.0,-12.0)/(+5.0,+15.0,-15.0)/ (+16.0,+48.0,-16.0)(V)
Output current	(4.0,2.0,0.5)/(4.0,2.0,0.5)/(4.0,1.5,0.5)/(2.0,0.15,2.0)(A)
Output power	46.5W for 13A,50.0W for 13D,50.0W for 14E,71.2W for 58F
Average active efficiency	>83.5%
Efficiency at low load (10 %)	>79.0 %(typ)
No-load power consumption	<0.30W

Model identifier	GC30B/E/U-(0/1/11/2/4/5/6)P1J
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	4.2/5.6/7.2/8.4/14.3/16.8/28.6(V)
Output current	4.0/3.99/3.0/3.0/2.09/1.6/1.04(A)
Output power	16.8W for 4.2V,22.38W for 5.6V,21.6W for 7.2V, 25.2W for 8.4V,30.0W for 14.3V,27.0W for 16.8V, 30.0W for 28.6V
Average active efficiency	>55% for 4.2V , > 70% for other
Efficiency at low load (10 %)	>52% for 4.2V , > 67% for other (typ)
No-load power consumption	<1.0W

Model identifier	SGA12-(5/7.5/9/12/15/18/24/48)
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/7.5/9.0/12.0/15.0/18.0/24.0/48.0 (V)
Output current	2.4/1.6/1.33/1.0/0.8/0.66/0.5/0.25 (A)
Output power	12W
Average active efficiency	>82.96 %
Efficiency at low load (10 %)	>75.0 %(typ)
No-load power consumption	<0.10W

Installatiehandleiding

Model identifier	SGA18-(5/9/12/15/18/24/48)
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/9.0/12.0/15.0/18.0/24.0/48.0 (V)
Output current	3.0/2.0/1.5/1.2/1.0/0.75/0.375 (A)
Output power	15W for 5.0V, 18.0W for other
Average active efficiency	>84.1 % for 5V, >85.0% for other
Efficiency at low load (10 %)	>78.5 %(typ)
No-load power consumption	<0.10W

Model identifier	SGA25-(5/7.5/9/12/15/18/24/48)
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/7.5/9.0/12.0/15.0/18.0/24.0/48.0 (V)
Output current	4.0/2.93/2.77/2.08/1.66/1.38/1.04/0.52 (A)
Output power	20W for 5.0V, 22W for 7.5V, 25.0W for other
Average active efficiency	>85.4% for 5V, >86.35% for other
Efficiency at low load (10 %)	>81.0 %(typ)
No-load power consumption	<0.10W

Model identifier	SGA40-(5/9/12/15/18/24/48)
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/9.0/12.0/15.0/18.0/24.0/48.0 (V)
Output current	5.0/4.44/3.33/2.66/2.22/1.67/0.84 (A)
Output power	25W for 5.0V, 40.0W for other
Average active efficiency	>86.35% for 5V, >87.6% for other
Efficiency at low load (10 %)	>85.0 %(typ)
No-load power consumption	<0.10W

Installatiehandleiding

Model identifier	SGA60-(5/7.5/9/12/15/18/24/48)
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/7.5/9.0/12.0/15.0/18.0/24.0/48.0 (V)
Output current	6.0/6.0/5.5/5.0/4.0/3.33/2.5/1.25 (A)
Output power	30W for 5.0V, 45W for 7.5V, 50W for 9.0V, 60.0W for other
Average active efficiency	>86.95% for 5V, >87.73% for 7.5V, >89.0% for other
Efficiency at low load (10 %)	>84.0 %(typ)
No-load power consumption	<0.21W

Model identifier	GE12I-(5/7.5/9/12/15/18/24)
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/7.5/9.0/12.0/15.0/18.0/24.0 (V)
Output current	2.0/1.33/1.33/1.0/0.8/0.83/0.625 (A)
Output power	10W for 5.0/7.5V, 12W for 9/12/15V, 15W for other
Average active efficiency	>81.95% for 5.0/7.5V, >82.96% for 9/12/15V, >84.13% for other
Efficiency at low load (10 %)	>72.1 %(typ)
No-load power consumption	<0.10W

Model identifier	GE18I-(5/7.5/9/12/15/18/24/48)
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/7.5/9.0/12.0/15.0/18.0/24.0/48.0 (V)
Output current	2.4/1.73/2.0/1.5/1.2/1.0/0.75/0.375 (A)
Output power	12W for 5.0V, 13W for 7.5V, 18W for other
Average active efficiency	>82.96% for 5.0V, >83.38% for 7.5V, >85.00% for other
Efficiency at low load (10 %)	>75.1 %(typ)
No-load power consumption	<0.10W

Installatiehandleiding

Model identifier	GE24I-(5/7.5/9/12/15/18/24/48)
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/7.5/9.0/12.0/15.0/18.0/24.0/48.0 (V)
Output current	3.0/2.0/2.22/2.0/1.6/1.33/1.0/0.5 (A)
Output power	15W for 5.0/7.5V, 20W for 9.0V, 24W for other
Average active efficiency	>84.13% for 5.0/7.5V, >85.47% for 9.0V, >86.20% for other
Efficiency at low load (10 %)	>75.8 %(typ)
No-load power consumption	<0.10W

Model identifier	GE30I-(12/15/18/24)
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	12.0/15.0/18.0/24.0 (V)
Output current	2.5/2.0/1.66/1.25 (A)
Output power	30W
Average active efficiency	>86.95%
Efficiency at low load (10 %)	>83.7 %(typ)
No-load power consumption	<0.10W

Model identifier	GEM06I05-P1J/USB,GEM06I (06/07/09/12/15/18/24) -P1J
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/6.0/7.5/9.0/12.0/15.0/18.0/24.0(V)
Output current	1.2/1.0/0.8/0.66/0.5/0.4/0.33/0.25(A)
Output power	6.0W for all
Average active efficiency	>70% for 5.0V , > 74% for other
Efficiency at low load (10 %)	>66 %(typ)
No-load power consumption	<0.30W

Installatiehandleiding

Model identifier	GE40I-(5/7.5/9/12/15/18/24/36/48)
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/7.5/9.0/12.0/15.0/18.0/24.0/36.0/48.0 (V)
Output current	4.0/2.66/3.3/3.3/2.7/2.2/1.67/1.00/0.83 (A)
Output power	20W for 5.0/7.5V, 30W for 9.0V, 40W for other
Average active efficiency	>85.47% for 5.0/7.5V, >86.92% for 9.0V, >87.58% for other
Efficiency at low load (10 %)	>77.3 %(typ)
No-load power consumption	<0.10W

Model identifier	GSM12E/GEM12I-(5/7.5/9/12/15/18/24/48)
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/7.5/9.0/12.0/15.0/18.0/24.0/48.0 (V)
Output current	1.6/1.33/1.0/0.8/0.66/0.5/0.25 (A)
Output power	12W
Average active efficiency	>82.96%
Efficiency at low load (10 %)	>72.96%(typ)
No-load power consumption	<0.10W

Model identifier	GEM18I-(5/9/12/15/18/24/48)
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/9.0/12.0/15.0/18.0/24.0/48.0 (V)
Output current	3.0/2.0/1.5/1.2/1.0/0.75/0.375 (A)
Output power	15W for 5.0V, 18.0W for other
Average active efficiency	>84.1 % for 5V, >85.0% for other
Efficiency at low load (10 %)	>81.0%(typ)
No-load power consumption	<0.10W

Installatiehandleiding

Model identifier	GEM30I-(5/7.5/9/12/15/18/24/48)
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/7.5/9.0/12.0/15.0/18.0/24.0/48.0 (V)
Output current	4.0/3.33/3.33/2.5/2.0/1.66/1.25/.625 (A)
Output power	20W for 5.0V, 25W for 7.5V, 30.0W for other
Average active efficiency	>85.47% for 5V, >86.35% for 7.5V, >86.95% for other
Efficiency at low load (10 %)	>81.0 %(typ)
No-load power consumption	<0.10W

Model identifier	GEM40I-(5/9/12/15/18/24/48)
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/9.0/12.0/15.0/18.0/24.0/48.0 (V)
Output current	5.0/4.0/3.33/2.66/2.22/1.66/0.83 (A)
Output power	25W for 5.0V, 36W for 9.0V, 40.0W for other
Average active efficiency	>86.35% for 5V, >87.40% for 9.0V, >87.59% for other
Efficiency at low load (10 %)	>85.0 %(typ)
No-load power consumption	<0.10W

Model identifier	GEM60I-(5/7.5/9/12/15/18/24/48)
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/7.5/9.0/12.0/15.0/18.0/24.0/48.0 (V)
Output current	6.0/6.0/5.5/4.5/4.0/3.33/2.5/1.25 (A)
Output power	30W for 5.0V, 45W for 7.5V, 50W for 9.0V, 54W for 12V, 40.0W for other
Average active efficiency	>86.95% for 5V, >87.73% for 7.5V, >89.0% for other
Efficiency at low load (10 %)	>83.0 %(typ)
No-load power consumption	<0.21W

Installatiehandleiding

Model identifier	NGE12E/U/I05-P1J/USB,NGE12E/U/I (09/12/15/18/24)-P1J
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/9.0/12.0/15.0/18.0/24.0(V)
Output current	2.4/1.33/1.0/0.8/0.83/0.625(A)
Output power	15W for 18/24V output,12W for other
Average active efficiency	>82% for 5V,>86% for other
Efficiency at low load (10 %)	>64.5% for 5V,>73.5% for other
No-load power consumption	<0.075W
Protective current (input)	2A

Model identifier	NGE18E/U/I(05/09/12/15/18/24)-P1J
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/9.0/12.0/15.0/18.0/24.0(V)
Output current	3.0/2.0/1.5/1.2/1.0/0.75(A)
Output power	15W for 5V output,18W for other
Average active efficiency	>82% for 5V,>87% for other
Efficiency at low load (10 %)	>78% for 5V,>79.5% for other
No-load power consumption	<0.075W
Protective current (input)	2A

Model identifier	NGE30E/U/I(05/09/12/15/18/24/48)-P1J
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/9.0/12.0/15.0/18.0/24.0/48.0(V)
Output current	4.0/3.33/2.5/2.0/1.66/1.25/0.63(A)
Output power	20W for 5V output,30W for other
Average active efficiency	>82% for 5V,>87% for other
Efficiency at low load (10 %)	>79% for 5V,>83.5% for other
No-load power consumption	<0.075W
Protective current (input)	3.15A

Installatiehandleiding

Model identifier	NGE45E/U/I(05/09/12/15/18/24/48)-P1J
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/9.0/12.0/15.0/18.0/24.0/48.0(V)
Output current	5.63/4.5/3.75/3.0/2.5/1.88/0.94(A)
Output power	28.1W for 5V output,40.5W for 9V OUTPUT,45W for other
Average active efficiency	>84% for 5V,>87% for other
Efficiency at low load (10 %)	>80% for 5V,>85% for other
No-load power consumption	<0.075W
Protective current (input)	3.15A

Model identifier	NGE65E/U/I(05/09/12/15/18/24/48)-P1J
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/9.0/12.0/15.0/18.0/24.0/48.0(V)
Output current	6.0/5.96/4.88/4.34/3.62/2.71/1.36(A)
Output power	30W for 5V output,53.6W for 9V OUTPUT,58.5W for 12V OUTPUT,65W for other
Average active efficiency	>84% for 5V,>87% for other
Efficiency at low load (10 %)	>80% for 5V,>85% for other
No-load power consumption	<0.075W
Protective current (input)	3.15A

Model identifier	NGE90E/U/I(12/15/18/24/48/55)-P1J
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	12.0/15.0/18.0/24.0/48.0/55.0(V)
Output current	6.25/5.5/5.0/3.75/1.875/1.64(A)
Output power	75/82.5/90/90/90/90.2(W)
Average active efficiency	>90%
Efficiency at low load (10 %)	>86% for 12V,>88% for other
No-load power consumption	<0.1W
Protective current (input)	3.15A



Installatiehandleiding

Model identifier	NGE100/NGE100U
Input voltage	230Vac
Input AC frequency	50Hz
Output voltage	5.0/9.0/12.0/15.0/20.0(V)
Output current	USB C1/2(5.0V,9.0V,12.0V,15.0V) for 3A, USB C1/2 20V for 5A,USB A1/2(5.0V for 3A,9.0V for 2A,12V for 1.5A,20V for 0.9A)
Output power	100W
Average active efficiency	>88.5%
Efficiency at low load (10 %)	83%forC1:20*0.5
No-load power consumption	<0.3W
Protective current (input)	3.15A
Voor gedetailleerde informatie kunt u de onderstaande QR-code scannen	
	

Manufacturer :

MEAN WELL ENTERPRISES Co., LTD.
No.28, Wuquan 3rd Rd., Wugu Dist.,
New Taipei City 24891, Taiwan
Tel: +886-2-2299-6100
Web: www.meanwell.com

Branch Office :

China

MEAN WELL (GUANGZHOU)
ENTERPRISES Co., LTD.
No.11, Jingu South Road, Huadong
Town, Huadu Distric, Guangzhou,
Gungzhou, China
Tel: +86-20-3773-7100
Web: www.meanwell.com.cn

China

SUZHOU MEAN WELL
TECHNOLOGY Co., LTD.
No.269 Changping Rd. , Huangdai
Town, Xiangcheng District
Suzhou, Jiangsu Province, China
Post Code: 215152
Tel: +86-512-6508-8600
Web: www.meanwell.cc

U.S.A.

MEAN WELL USA, INC.
44030 Fremont Blvd., Fremont,
CA 94538, U.S.A.
Tel: +1-510-683-8886
Web: www.meanwellusa.com

Europe

MEAN WELL EUROPE B.V.
Langs de Werf 8, 1185XT Amstelveen, The
Netherlands
Tel: +31-20-758-6000
Web: www.meanwell.eu

2024.01.02

ISO-9001 CERTIFIED
Your Reliable Power Partner



Declaration of China RoHS Conformity

In order to reduce the impacts on the environment and take the more responsibility for protecting the earth, MEAN WELL is confirming and announcing the conformity to China RoHS, an Administrative Measures for the Restriction of the Use of Hazardous Substances in Electrical and Electronic Products.

Environment Friendly Use Period Label

Observing SJT 11364-2024, Marking for the Restricted Use of Hazardous Substances in Electronic and Electrical Products

Observing SJ/Z 11388-2009, General Guidelines of Environment-friendly Use Period of Electronic Information Products Appendix B, adopting table look-up to verify the Environment Friendly Use Period

Names and Contents of Hazardous Substances Lists

Part Name	Hazardous Substances									
	Lead	Mercury	Cadmium	Hexavalent chromium	Polybrominated biphenyls	Polybrominated diphenyl ethers	Bis(2-ethylhexyl) phthalate	Dibutyl phthalate	Dibutyl phthalate	Diisobutyl phthalate
	(Pb)	(Hg)	(Cd)	(Cr ⁶⁺)	(PBB)	(PBDEs)	(DEHP)	(DBP)	(DBP)	(DIBP)
PCB and its components	X	O	O	O	O	O	O	O	O	O
Metal structure parts	X	O	O	O	O	O	O	O	O	O
Plastic structure parts	O	O	O	O	O	O	O	O	O	O
Accessories	O	O	O	O	O	O	O	O	O	O
Cables	X	O	O	O	O	O	O	O	O	O
O: The concentration of the hazardous substances within the homogeneous material of that product is less than the concentration limits set by GB/T 26572-2011. X: The concentration of the hazardous substances within the homogeneous material of that product is over the concentration limits set by GB/T 26572-2011; however, it follows the standard advised by 2011/65/EU.										



MEAN WELL ENTERPRISES CO., LTD.

No.28, Wuquan 3rd Rd., Wugu Dist., New Taipei City 24891, Taiwan (R.O.C.)

Tel: +886-2-2299-6100

Fax: +886-2-2299-6200

E-mail: info@meanwell.com

<http://www.meanwell.com>

Declaration of China VOC Conformity

In order to reduce the impacts on the environment and take the more responsibility for protecting the earth, MEAN WELL is confirming and announcing the conformity to China's Standardization Administration Releases VOC Standards

Standard No.	Name of the Standard
GB 30981-2020	Limit of harmful substances of industrial protective coatings
GB 33372-2020	Limits for volatile organic compounds content in adhesive
GB 38507-2020	Limits for volatile organic compounds (VOCs) In printing ink
GB 38508-2020	Limits for volatile organic compounds content in cleaning agents

ISO-9001 CERTIFIED

Your Reliable Power Partner



MEAN WELL ENTERPRISES CO., LTD.

No.28, Wuquan 3rd Rd., Wugu Dist., New Taipei City 24891, Taiwan (R.O.C.)

Tel: +886-2-2299-6100

Fax: +886-2-2299-6200

E-mail: info@meanwell.com

<http://www.meanwell.com>

Declaration of Five PBT TSCA Conformity

In order to reduce the impacts on the environment and take the more responsibility for protecting the earth, MEAN WELL hereby confirms that MEAN WELL product series comply with Use and Risk Management for Five PBT Chemicals under TSCA section 6(h)

CAS No.	Substance Name
1163-19-5	Decabromodiphenyl ether (DecaBDE)
68937-41-7	Phenol, isopropylated, phosphate (3:1) PIP (3:1)
732-26-3	2,4,6-Tris (tert-butyl) phenol (2,4,6-TTBP)
133-49-3	Pentachlorothiophenol (PCTP)
87-68-3	Hexachlorobutadiene (HCBD)

ISO-9001 CERTIFIED

Your Reliable Power Partner